

## LISTENING AND RESPONDING [1]

### Reviewing messages

Review:

- New voice messages [1]
- Saved voice messages [1] [2]
- New e-mail messages [2]
- Saved e-mail messages [2] [2]
- New fax messages [3]
- Saved fax messages [3] [2]
- Deletion pending messages [4]
- Administrative messages [9]

**TIP:** Use playback controls as desired (see reverse).

### Forwarding a message

- At end of message [6]
- To forward message...
  - ...Without comment [1]
  - ...With comment [2]
- When finished [#]
- Specify address
- When finished [#]
- After entering all addresses [#] [#]
- Send message [#]

### Replying to a message

- At end of message
  - Reply to sender [8] [1]
  - Reply to all [8] [2]
  - Reply to sender with original [8] [3]
  - Reply to all with original [8] [4]
- Record reply
- When finished [#] [#]

### Replying by calling internal caller

- At end of message [8] [8]

## PRINTING A FAX OR E-MAIL [1]

### Printing a message after reviewing

At the end of the message, choose:

- To print to default fax number [2] [1]
- To print to alternate fax number [2] [2]
- To print from the fax machine you are using [2] [3]
- To send a fax to another recipient [2] [4]

### Printing messages before reviewing

Print:

- All new fax messages [8] [1]
- A list of all messages in inbox [8] [2]
- A list of all new messages in inbox [8] [3]

Choose:

- To print to default fax number [1]
- To print to alternate fax number [2]
- To print from the fax machine you are using [3]
- To send a fax to another recipient [4]

## PERSONALIZING YOUR MAILBOX [4]

### Recording or changing prompts or greetings [1]

1. Choose:

- Personal greeting [1]
  - Extended Absence greeting [2]
  - Optional greetings [3]
  - Please Hold prompt [5]
  - Name prompt [6]
2. For optional greetings only, enter the greeting number [1-9]
3. If Multilingual Call Answer is enabled, select a language [1-3]
4. If the prompt or greeting is already recorded:
- Accept recording [1]
  - Rerecord [2]
  - Delete prompt or greeting [3]

### Using special features [2]

To set:

- Find Me on or off [2] [1]
- Call Me on or off [3] [1]
- Caller requested notification on or off [4] [1]
- Automatic notification on or off [4] [2]
- Call screening [5]
- Intercom paging [7]

To review active options [9]

### Changing call handling [3]

- Block all incoming calls [1]
- Activate optional greetings [4]
- Review current greeting rules [8]
- Delete all greeting rules [9]

### Setting up rules for optional greetings

- Hear rule [0]
- Activate for internal calls → external calls → all calls (rotate) [1]
- Activate for busy → no answer → busy or no answer (rotate) [2]
- Activate for business hours → out of business hours → any time (rotate) [3]
- Delete current greeting rule [7]
- Accept greeting rule [#]

### Setting a default fax number [4]

Enter the new telephone number

- Confirm [1]
- Change [2]

### Recording or changing announcements [5]

Enter the announcement number

OR

If announcement is already recorded:

- Accept recording [1]
- Rerecord [2]
- Delete announcement [3]

### Managing personal distribution lists [6]

- Create list [1]
- Edit list [2]
- Delete list [3]
- Review active lists [4]

### Setting up Personal Operator [7]

- Change Personal Operator [1]
- Change Schedule [2]

### Changing your password [9]

- Enter new password, followed by [#]
- Reenter new password, followed by [#]

## RECORDING AND SENDING [2]

### Creating a new voice message

- Record message
- When finished [#]
- Enter destination address, followed by [#]
- After entering all addresses [#] [#]
- Specify delivery options (see below)
- Send [#]

To cancel recording [\*]

To spell name [#]

### Delivery options

- Send immediately [#]
- Mark as priority/not priority [2]
- Mark for future delivery [4]
- Mark as private [5]

## CALL ANSWERING

When answering Find Me, Call Me, or screened calls:

- To accept a call [#]
- To reject a call [1]
- To replay a Find Me or Call Me message [3]

## SHORTCUTS

Bypass welcome greeting [#]

When reviewing messages, skip:

- From New to Saved to Deleted [#] [#]
- To start of message [1] [1]
- To end of message [3] [3]

## GENERAL TIPS

### Pressed the wrong key?

To cancel or back up, press [\*]

### Go back to Main menu?

Press [\*] repeatedly until you hear "Main menu..."

### Exiting your mailbox

Return to the Main menu, and press [\*] again, or hang up.

### Want to hear the menu again?

While listening to a menu, press [0]

**NOTE:** Your system may not support all features. For more information, check with your system administrator.



## Aria® Telephone User Interface for Avaya Modular Messaging QUICK REFERENCE GUIDE

Copyright © 2011, Avaya, Inc. All rights reserved. All trademarks identified by ® and ™ are registered trademarks or trademarks respectively of Avaya Inc. All other trademarks are the properties of their respective owners.

**Disclaimer:** Avaya is not responsible for any modifications, additions or deletions to the original published version of this documentation unless such modifications, additions or deletions were performed by Avaya. Customer and/or end user agree to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation to the extent made by the customer or end user.

AUGUST 2011

## ABOUT THIS GUIDE

This quick reference guide provides step-by-step instructions on how to perform important tasks when using the Modular Messaging system through the Aria® telephone user interface (TUI). For additional information, consult the Modular Messaging TUI guide.

**Note:** Depending on the way your system is set up, some features in this guide may not be available.

\* Changes to next language only  
if your system supports multiple languages.

## Accessing your mailbox

From your office extension:

1. Call the system access number.
2. Enter your password followed by [#].

From someone else's office extension or from outside of your office:

1. Call the system access number.
2. Do one of the following:
  - If you are prompted to enter the password for the extension from which you are calling, press [\*] [#].
  - If you are prompted to enter the extension of the person you are calling, press [#].
3. Enter your mailbox number.
4. Enter your password followed by [#].

